TD61-2487A



WirelessIP 5000 Web Configuration Manual (v2.0.0)

Hitachi Cable, Ltd.

HITACHI CABLE, LTD

<u>1.</u>	WWW MANAGEMENT INTERFACE 1	1
1.1	SUMMARY 1	1
1.2	BOOTUP1	l
1.3	ACCESS AUTHORITY 1	L
<u>2.</u>	GENERAL USER MENU	<u>3</u>
2.1	1 Display Items	3
MC	DEL: DISPLAYS THE MODEL NAME	3
2.2.	1 CHANGING THE PASSWORD	1
2.3	1 DISPLAY ITEMS	5
2.3	2 SEARCHING/EDITING/DELETING PHONEBOOK	5
2.3	3 NEW PHONEBOOK REGISTRATIONS	5
2.3	3 GROUP REGISTRATIONS	5
2.3.	4 EDITING/DELETING GROUPS	5
<u>3.</u>	MANAGEMENT USER MENU	<u>7</u>
3.1	MAIN PAGE	7
3.1.	1 DISPLAY ITEMS	7
3.2	CONFIGURATION	3
3.3	SYSTEM SETUP 10)
3.3.	4 REBOOT	1
3.4	NETWORK SETUP	2
3.4	1 CONFIGURATION CHANGES	2
3.4	2 SETTING CONFIGURATIONS	2
3.5	DOWNLOAD CONFIGURATION FILE	2
3.5.	1 DOWNLOADING CONFIGURATIONS	2

1. WWW Management Interface

1.1 Summary

WirelessIP 5000 (herein referred to as "the handset") can be configured via the Internet. By using the WWW Management Interface, you can configure detailed settings that cannot be set via the handset itself.

1.2 Bootup

To start up the WWW Management Interface, start the web browser on each client handset and access this address: http://<host>:cport>/ For <host>, insert the IP address or host name for the handset that you want to configure, and for cport>, insert the port number (the port number is 8080, and cannot be omitted).

1.3 Access Authority

The certification screen for login displays in the WWW Management Interface. Login by entering the username/password set for the handset.

Enter Netv	Enter Network Password			
? >	Please type yo	our user name and password.		
١	Site:	172.16.9.165		
	Realm	WirelessIP5000		
	<u>U</u> ser Name			
	<u>P</u> assword			
	□ <u>S</u> ave this p	password in your password list		
		OK Cancel		

· · · · · · · · · · · · · · · · · · ·	(Figure	1)
---------------------------------------	---------	----

	General User	Management User
Username	user	admin
Password	0000	000000
Authority	Browse Handset Information	Change Handset Settings
	Edit Phonebook	• Upgrade FW/Config
	 Change User Password 	Change Admin Password
		Stop WEBServer

Note 1: The same user cannot log in to more than one browser (client) at the same time. Simultaneous login of different users is permitted.

2. General User Menu

Only the browsing of basic information, editing the phonebook, and editing of the user password are permitted.

2.1 Main Page

This screen displays the handset's software version, TCP/IP settings, and other basic information.

A Web Configuration - Microsoft Inte	rnet Explorer	
File Edit View Favorites Tools	Help	
	Search Gal Favorites Milistory	
		Ac. Index »
Agdress F http://1/2.16.9.165:8080/lo		Cr Go Links
	Main Page Phonebook	<u>A</u>
WirelessIF • <u>Phonebook</u> • <u>Change Password</u>	95000 Web Configuration Too	
Softwar	e Specification	
MODEL	WirelessIP5000	
SOFTWARE VERSION	v2.0.0	
IP ADDRESS	172.16.9.151	
NETMASK	255.255.255.0	
GATEWAY	172.16.9.1	
MAC ADDRESS	00:03:2A:00:24:14	
		<u>×</u>
🔊 Done	🔵 🚺 💓 Interne	t (Figure 2)

2.1.1 Display Items

MODEL: Displays the model name SOFTWARE VERSION: Displays the handset's software version IP ADDRESS: Displays the IP address of the handset NETMASK: Displays the netmask of the handset GATEWAY: Displays the default gateway of the handset MACADDRESS: Displays the MAC address of the handset

2.2 Change Password

Changes the user password for the handset

🚰 Web Configuration - Microsoft Internet Explorer		
<u> </u>		
📙 🖙 Back 🔹 🤿 🖌 🔞 🕅 🖓 Search 💿 Favorites 🖓 History 🛛 🔂 🕶 🎒		
Address 🛃 http://172.16.9.165:8080/load.html	💌 🤗 Go 🛛 Links »	
Main Page Phonebook	<u>_</u>	
Change Password		
• ID user		
Old Password		
New Password		
Retype		
CHANGE VALUE RESET		
a Done	S Internet	(Figure 3)

2.2.1 Changing the Password

- 1. Enter the username into the ID field.
- 2. Enter the old password.
- 3. Enter the new password.
- 4. Re-enter the new password (for confirmation).
- 5. Press the "CHANGE VALUE" button.

* To reset the entered information, press the "RESET" button.

2.3 Phonebook

Searches/configures/deletes the handset's phonebook data.

Web Configuration - Microsoft Internet Explorer		1
Eile Edit View Favorites Iools Help	100 M	
😓 Back 🔹 🤿 🖌 🔯 🖓 🖓 Search 🕋 Favorites 🛛 🖓 History 🛛 🖏 🛀 🎒		
Address 😰 http://172.16.9.165:8080/load.html	▼ 🖉 Go 🛛 Links ≫	
	A	
<u>Main Page</u> <u>Phonebook</u>		
Phonebook		
Phonebook Menu List		
Search by Index		
Search by Name		
 Search by Number Search by Group 		
New Number		
Edit Group		
	-	
Done	🔹 Internet	(Figure

2.3.1 Display Items

- Search by Index: Searches/configures/deletes by speed dial.
- Search by Name: Searches/configures/ deletes by name.
- Search by Number: Searches/configures/ deletes by telephone number.
- Search by Group: Searches/configures/ deletes by group.
- New Number: Registers new number to the phonebook data.
- Edit Group: Searches/configures/deletes groups.

2.3.2 Searching/Editing/Deleting Phonebook

- 1. Select search method. (Index, Name, Number, Group).
- 2. Enter search information and press "SEARCH" button.
- * If no search information is entered and the "SEARCH" button is pressed, the entire phonebook displays.
- 3. The phonebook data matching the search information displays.
- 4. Select the displayed phonebook data to edit/delete the phonebook.

2.3.3 New Phonebook Registrations

- 1. Select the "New Number" button.
- 2. Enter the Name, Read Name, Phone Number, Speed Dial, and Group.
- 3. Press the "SAVE and CONTINUE" button to create another phonebook entry.
- 4. Press the "SAVE" button to register into the phone book and return to the Phonebook menu.

2.3.3 Group Registrations

- 1. Press the "Edit Group" button.
- 2. Enter the group name to register into the New Group and press the "SAVE" button.

2.3.4 Editing/Deleting Groups

- 2. Select the group name to edit/delete from among the displayed groups.
- 3. To change a group name, enter the group name to change and press the "CHANGE" button.
- 4. To delete a group name, press the "DELETE" button.

3. Management User Menu

Allows terminal settings to be changed, the FW/config can be upgraded, the admin password can be changed and the WEBServer can be stopped.

3.1 Main Page

This screen displays the handset's software version, TCP/IP settings, and other basic information.



3.1.1 Display Items

MODEL: Displays model name SOFTWARE VERSION: Displays software version of the handset IP ADDRESS: Displays IP address of the handset NETMASK: Displays netmask of the handset GATEWAY: Displays default gateway of the handset MACADDRESS: Displays MAC address of the handset

3.2 Configuration

This screen is used to perform handset configuration.



August Ca-Gaunctica Minaca 0. Takawa te Fundanan	
File Edit View Exports Tools Help	
y Back → → ∞ ② ③ ☆ ③ Search ⓐ Favorites ੴHistory □ □ → ∰	
Address 🙆 http://172.16.9.165:8080/section.html?sid=000	Links »
Main Page Configuration System Setup Network Setup	- -
Language (0~65535) 1 Use DNS SRV	-
🙋 Done 👘 👘 Internet	(Figure 7

3.2.1 Configuration Changes

- 1. Select the SECTION to change.
- 2. Edit the ENTRY value.
- 3. Press the "CHANGE VALUE" button and change the settings.
- 4. Press the "YOU MUST REBOOT" button and reboot the handset.
- * The settings will not take effect without rebooting the handset.
- * There are some items for which the "YOU MUST REBOOT" button is not displayed. In those cases the setting is updated after the "CHANGE VALUE" button is pressed.

3.3 System Setup

Allows the WirelessIP 5000's FW/Config to be upgraded, the password of the Admin user can be changed, and the WebServer can be stopped.

🖉 Web Configuration - Microsoft Internet Explorer	
Eile Edit View Favorites Tools Help	
Address 🖉 http://172.16.9.165:8080/sys.html	iks »
Main Page Configuration System Setup Network Setup	-
System Setup	
REBOOT	
Load & Upgrade Change Password WebServer Stop	
Done Internet	(Figure 8)

3.3.1 Load & Upgrade

Upgrades the firmware and configuration of the WirelessIP 5000.



3.3.1.1 Upgrading Methods

- 1. Enter the IP address of the TFTP server where the firmware is located.
- 2. Indicate the type of upgrade (software/config).
- 3. Press the "DO UPGRADE" button.

3.3.2 Change Password

Changes the Admin password of the handset.

3.3.3 WebServer Stop

Stops the WebServer from accessing the WWW Management Interface. Warning: Access via WWW is disabled when the "WebServer Stop" button is pressed.

3.3.4 Reboot

Reboots the handset.

3.4 Network Setup

Configures SIP/Network.

3.4.1 Configuration Changes

- 1. Edit the menu for the settings to be changed.
- 2. Press the "CHANGE VALUE" button.

3.4.2 Setting Configurations

- 1. Select the "ADD [New Network Profile]" button.
- 2. Enter the network information and press the "ADD" button.
- * Up to 5 config files can be created

3.5 Download Configuration File

A WirelessIP configuration file can be downloaded to a PC.

3.5.1 Downloading Configurations

- 1. Select the "Download Configuration File" button.
- 2. Enter the file name and save to the PC.

Copyright© 2005 Hitachi Cable, LTD. Otemachi Building, 6-1 Otemachi 1-chome, Chiyoda-ku, Tokyo 100-8166, Japan

First Edition, February 2005 Second Edition, August 2005